

## MT-7068 All-In-One Toner & Probe Kit



### Description:

The MT-7068 All-in-one Toner & probe Kit lets you use Toner and Probe to validate and troubleshoot wiring on RJ11/RJ45 cables and connectors, USB, F, BNC, and RCA connectors, and it also supplied with alligator clips to work with. The MT-7068 Toner detects telephone and Ethernet service, indicates polarity and active line numbers on voice circuits, and indicates active pair number on Ethernet circuits. The MT-7068 Toner and Probe also provide standard functions such as visual and audible signal strength indication, analog toning/detection, and continuity testing. It is ideal for all maintenance fields of

telecommunication, networking, datacom, Audio/Video, cable TV, and all weather cabling , etc.

## Features:

- . Locates cables quickly and easily
- . Locates hidden cables
- . Isolates the right cable or pair fast
- . Overcome noise and save time
- . Tone on live networks safely and effectively
- . Verify conductor continuity with cable map
- . Identify and troubleshoot cable services

## Applications:

- . Copper cabling media, including shielded (STP) and UTP cable
- . 75 or 50 Ohm coaxial cable
- . 10 Base-T or 10/100 Base-T datacom net works
- . Two conductor control, security, generic cabling
- . POTS telecom service



Copper cabling detecting, including shielded (STP) and UTP cable



10 Base-T or 10/100 Base-T datacom networks



Locates and isolates cables quickly and easily



Accessories: 1 zipper bag, 2 RJ-45 cables, 2 BNC connectors, and 2 RCA connectors

## Specifications:

### MT-7068-T Toner Specifications

Tone frequency	1KHz
Tone mode	ONE/TWO-note tone
Compatible connectors	RJ-45/RJ-11/USB/F/BNC/RCA/Alligator Clips
Continuity test	>300Ω
Talk battery voltage	6V into 600Ω
Function selection	5-position rotary switch
Cable map indication	8 LED indicators
Voltage protection	100V
Low battery display	6.5V
Battery type	9V (6F22)

Dimension (LxWxD)	140x70x30mm
-------------------	-------------

### **MT-7068-R Receiver Specifications**

Frequency	1KHz
Compatible connectors	RJ-45/RJ-11/USB/F/BNC/RCA
Ear jack	1
Signal status indication	8 LED indicators
Cable map indication	8 LED indicators
Low battery display	6.5V
Battery type	9V (6F22)
Dimension (LxWxD)	250x52x33mm